



**Caution**  
**Equipment Hazard:** All equipment should be powered down prior to making wiring connections and changing switch positions.

**Notes**

1. Power off the amplifier and reduce the volume by turning the Tel Page Level Control counter-clockwise before connecting the CyberData device and powering the amp back on.
  2. Power off the amplifier prior to connecting the CyberData device and turn the Tel Page Level Control fully counter-clockwise.
  3. Connect the CyberData device, and then power the amplifier back on.
  4. Slowly raise the Tel Page Level Control (clockwise) to adjust the volume.
- 2-conductor, shielded speaker wire is recommended.

**Page Port Connections**

Pin	Description
1	Fault Sense Input (Common).
2	Fault Sense Input (Sense).
3	Positive 600-Ohm Audio Output <sup>a</sup>
4	Negative 600-Ohm Audio Output <sup>a</sup>
5	Audio Ground Reference.
6	Relay Contact - Common <sup>b</sup>
7	Relay Contact - Normally Open <sup>b</sup>

a. The 600-Ohm audio output of the page port is also suited for interfaces with lower input impedances.  
 b. 1 Amp at 30 VDC for continuous loads.