



### Page Port Connections

Pin	Description
1	Fault Sense Input (Common).
2	Fault Sense Input (Sense).
3	Positive 600-Ohm Audio Output <sup>a</sup>
4	Negative 600-Ohm Audio Output <sup>a</sup>
5	Audio Ground Reference.
6	Relay Contact - Common <sup>b</sup>
7	Relay Contact - Normally Open <sup>b</sup>

### Notes

The Valcom V-1101A would stay as the amplifier / booster for the Valcom speakers (powered by the VP-4024B power supply) and the speakers would stay.

The SIP Paging Adapter needs to connect to the Valcom V-1101A in **Page Port Mode**. It is very important to not connect in **Loop Start Mode** as that can damage the device

2-conductor, shielded speaker wire is recommended.

a. The 600-Ohm audio output of the page port is also suited for interfaces with lower input impedances.

b. 1 Amp at 30 VDC for continuous loads.