



Notes

The Valcom V-1101A would stay as the amplifier / booster for the Valcom speakers (powered by the VP-4024B power supply) and the speakers would stay.

The VoIP Paging Server needs to connect to the Valcom V-1101A in **Page Port Mode**. It is very important to not connect in **Loop Start Mode** as that can damage the device

2-conductor, shielded speaker wire is recommended.

| Pin | Description |
|-----|--|
| 1 | Fault Sense Input (Common). |
| 2 | Fault Sense Input (Sense). |
| 3 | Positive 600-Ohm Audio Output ^a |
| 4 | Negative 600-Ohm Audio Output ^a |
| 5 | Audio Ground Reference. |
| 6 | Relay Contact - Common ^b |
| 7 | Relay Contact - Normally Open ^b |

a. The 600-Ohm audio output of the page port is also suited for interfaces with lower input impedances.

b. 1 Amp at 30 VDC for continuous loads.